

940 Receptacle angled rotatable

Speedtec - ready 8-pin Earth-to-Housing Connection according to VDE 0627 flange mount /Flange 40x40 Anti-vibration o-ring

C ED E 271 NN 00 00 0051 000 C G E 271 N 00 00 0051 000



Contact Arrangement mating view



Technical Data number of pins

power signal temperature range protection type rotation range 8 4 (3+PE) 4 -20 °C to 130 °C when connected IP 66/67 330°

Electrical Data rated current rated voltage rated insulation voltage (L-L)

 max.
 75 A*
 max.
 30 A*

 630V (AC/DC)
 250 V (AC/DC)
 6000 V
 4000 V

mating cycles

500

III

2000 m

power

Data according to VDE 0110/EN61984, Paragraph 6.19.2.2

signal

pollution degree over voltage category max. height for operation

Material

housing insulation insert seals zinc diecast / collinox PA 6.6 mod., UL 94/V0 FKM

Contacts (not part of product contents)

Tools (not part of product contents)


© 2018 TE Connectivity

TE Connectivity, TE connectivity (logo), intercontec (logo) and speedtec are trademarks.

While TE Connectivity (TE) has made every reasonable effort to ensure the accuracy of the information in this presentation, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties of merchantability or fitness for a particular purpose. The dimensions in this article are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications.

TE Connectivity Industrial GmbH Bernrieder Straße 15 94559 Niederwinkling, Deutschland Tel: +49 9962 2002-0 Fax: +49 9962 2002-70 E-Mall: intercontec@te.com Web: www.intercontec.biz





Main Dimensions Receptacle angled rotatable *for max. wire cross-section pay attention to the cross-section of used contacts