


AXICOM HF3 RELAY

RF SIGNAL RELAYS

INTRODUCTION

TE Connectivity's (TE) Axicom HF signal relays, small size electromechanical relays designed for high frequency signal transmission applications, are manufactured in a wide range of variants. The HF relays are designed as 1 changeover contact, giving them an operating signal range up to 3 GHz with excellent high frequency characteristics.



FEATURES

- Y-Design
- Frequency range DC to 3GHz
- Impedance 50Ω or 75Ω
- Small dimensions (14.6x7.2x10mm)
- 1 form C contact (1 changeover contact)
- Immersion cleanable
- Low power consumption (≤140mW)

APPLICATIONS

- Cable modems and linecards/ CATV
- Tabs
- Measurement and test equipment ATE
- Satellite / audio / video tuners
- Wireless base stations and antennas
- Switching boards

CONTACT DATA

Contact arrangement	1 form C, 1 CO		
Max. switching voltage	220 VDC, 250 VAC		
Rated current	2 A		
Limiting continuous current, 23°C	2 A		
Cuitabing navor	60 W, 62.5 VA,		
Switching power	50 W (2.5 GHz)		
Max. continuos RF-power, 23°C	50 W (2.5 GHz)		
Contact material	Ag, Au covered		
Minimum switching voltage	100 μV		
Initial contact resistance	<100 m Ω at 10 mA, 30 mV		
Operate time	typ. 3 ms, max. 5 ms		
Release time			
without diode in parallel	typ. 2 ms, max. 5 ms		
with diode in parallel	typ. 4 ms, max. 6 ms		
Bounce time	typ. 1 ms, max. 3 ms		
Duration of set/reset pulse min.	20 ms		
Mechanical endurance	10 ⁷ operations		

COIL DATA


Coil voltage	3 to 24 VDC


Coil code	Rated voltage VDC		Limiting voltage VDC		Coil resistance Ω±10%	Rated coil power mW
50 Ω v	ersion, n	nonostab	le, 1 coil			
51	3	2.25	6.5	0.30	64	140
52	4.5	3.38	9.80	0.45	145	140
53	5	3.75	10.90	0.50	178	140
54	6	4.50	13.00	0.60	257	140
55	9	6.75	19.60	0.90	574	140
56	12	9.00	26.10	1.20	1028	140
57	24	18.00	52.30	2.40	4114	140
75 Ω v €	ersion, n	nonostab	le, 1 coil			
01	3	2.25	6.5	0.30	64	140
02	4.5	3.38	9.80	0.45	145	140
03	5	3.75	10.90	0.50	178	140
04	6	4.50	13.00	0.60	257	140
05	9	6.75	19.60	0.90	574	140
06	12	9.00	26.10	1.20	1028	140
07	24	18.00	52.30	2.40	4114	140

Coil code	Rated voltage VDC		Limiting voltage VDC	Release voltage VDC	Coil resistance Ω±10%	Rated coil power mW
50 Ω v	ersion, b	istable, 1	coil			
71	3	2.25	9.20	-2.25	128	70
72	4.5	3.38	13.85	-3.38	289	70
73	5	3.75	15.30	-3.75	357	70
74	6	4.50	18.50	-4.50	514	70
75	9	6.75	27.70	-6.75	1157	70
76	12	9.00	37.00	-9.00	2057	70
77	24	18.00	74.00	-18.00	8228	70
50 Ω v €	ersion, bi	istable, 2	coils			
91	3	2.25	6.5	2.25	64	140
92	4.5	3.38	9.80	3.38	145	140
93	5	3.75	10.90	3.75	178	140
94	6	4.50	13.00	4.50	257	140
95	9	6.75	19.60	6.75	574	140
96	12	9.00	26.10	9.00	1028	140
97	24	18.00	52.30	18.00	4114	140
75 Ω ve	ersion, bi	stable, 1	coil			
21	3	2.25	9.20	-2.25	128	70
22	4.5	3.38	13.85	-3.38	289	70
23	5	3.75	15.30	-3.75	357	70
24	6	4.50	18.50	-4.50	514	70
25	9	6.75	27.70	-6.75	1157	70
26	12	9.00	37.00	-9.00	2057	70
27	24	18.00	74.00	-18.00	8228	70
75 Ω version, bistable, 2 coils						
41	3	2.25	6.5	2.25	64	140
42	4.5	3.38	9.80	3.38	145	140
43	5	3.75	10.90	3.75	178	140
44	6	4.50	13.00	4.50	257	140
45	9	6.75	19.60	6.75	574	140
46	12	9.00	26.10	9.00	1028	140
47	24	18.00	52.30	18.00	4114	140

All figures are given for coil without pre-energization, at ambient temperature +23°C.

COIL OPERATING RANGE





INSULATION DATA

	50 Ω version 75 Ω version		
Initial dielectric strength			
Between open contacts	600 V _{rms}		
Between contact and coil	1000 V _{rms}		
Initial surge withstand voltage			
Between open contacts	1000 V		
Between contact and coil	1500 V		

RF DATA


	50 Ω version	75 Ω version			
Isolation					
@ 100 MHz / 900 MHz	80 dB/72 dB	80 dB/72 dB			
@ 3 GHz	45 dB	40 dB			
Insertion loss					
@ 100 MHz / 900 MHz	0.03 dB / 0.12 dB	0.03 dB / 0.12 dB			
@ 3 GHz	0.35 dB	0.40 dB			
Voltage standing wave ratio (VSWR)					
@ 100 MHz / 900 MHz / 3 GHz	1.05 / 1.20 / 1.20	1.05 / 1.20 / 1.40			

OTHER DATA


Material compliance	EU RoHS/ELV, China RoHS, REACH, Halogen content refer to the Product Compliance Support Center at www. te.com/customersupport/ rohssupportcenter		
Ambient temperature	-55 °C to +85 °C		
Thermal resistance	< 165 K/W		
Category of environmental pro	tection		
IEC 61810	RT III - wash tight		
Degree of protection, IEC 60529	IP 67, immersion cleanable		
Vibration resistance (functional)	35 g, 10 Hz to 1000 Hz		
Shock resistance (functional), half sinus 11ms	50 g		
Shock resistance (destructive), half sinus 0.5ms	150 g		
Terminal type	SMT		
Weight	max. 2.5 g		
Resistance to soldering heat SI	МТ		
IEC 60068-2-58	250 °C/10 s		
Moisture sensitive level, JEDEC J-Std-020D	MSL3		
Ultrasonic cleaning	not recommended		
Packaging/unit	reel/400 pcs., box/400 or 2000 pcs.		


GRAPHS

Typical RF performance, 50Ω version




Typical RF performance, 50Ω version (continued)







Typical RF performance, 75 Ω version



Typical RF performance, 75 Ω version (continued)







TERMINAL ASSIGNMENT

TOP view on component side of PCB


Monostable



Bistable, 1 coil



Bistable, 2 coils




Note: Contacts are shown in reset condition. Contact position might change during transportation and must be reset before use.


PCB LAYOUT

TOP view on component side of PCB

50 Ω version




75 Ω version



DIMENSIONS

50 Ω version



Coplanarity<=0.10mm

ETE AXICOM CZ

1.27:8:1

5.08:8:1 5.08:8:1

6.35:8:15 6.35:8:15

HF3 xx 💠


zz VDC


WWCC

YYWW


3.81:8:1


2.54:0:1






75 Ω version











PROCESSING


PACKING











ORDERING INFORMATION



Coil

Coil code: please refer to coil versions table Performance type

5x	50Ω version, monostable 1coil
7x	50Ω version, bistable 1coil
9x	50Ω version, bistable 2coils
Ox	75Ω version, monostable 1coil
2x	75Ω version, bistable 1coil
4x	75Ω version, bistable 2coils

PRODUCT INFORMATION

TE Part Number	Arrangement	Version	Coil	Coil type	Part Number	
HF3 51				3VDC		1462051-1
HF3 52		orm C (1 CO) 50ohm	4.5VDC		1-1462051-6	
HF3 53			5VDC		1462051-2	
HF3 54	1 form C (1 CO)		6VDC	Monostable	1-1462051-7	
HF3 55			9VDC		1462051-3	
HF3 56			12VDC		1462051-4	
HF3 57			24VDC		1462051-5	
HF3 71			3VDC		1462051-6	
HF3 72	16 (1.60)	FO . l	4.5VDC	Distribute 1 and	1-1462051-8	
HF3 73	1 form C (1 CO)	50ohm	5VDC	Bistable 1 coil	1462051-7	
HF3 76			12VDC		1462051-9	
HF3 91			3VDC		1-1462051-1	
HF3 92			4.5VDC		2-1462051-0	
HF3 93	16 (1.60)	1 form C (1 CO) 50ohm	5VDC	Bistable 2 coils	1-1462051-2	
HF3 95	I form C (I CO)		9VDC		1-1462051-3	
HF3 96			12VDC		1-1462051-4	
HF3 97			24VDC		1-1462051-5	
HF3 01			3VDC		1462050-1	
HF3 02			4.5VDC		1-1462050-6	
HF3 03	1 form C (1 CO)	75ohm	5VDC	Monostable	1462050-2	
HF3 06	1		12VDC		1462050-4	
HF3 07			24VDC		1462050-5	
HF3 21			3VDC		1462050-6	
HF3 23	1 form C (1 CO)	75ohm	5VDC	Bistable 1 coil	1462050-7	
HF3 26			12VDC		1462050-9	
HF3 41			3VDC		1-1462050-1	
HF3 43	16	75 - 1	5VDC	Dietalala Carall	1-1462050-2	
HF3 46	1 form C (1 CO)	75ohm	12VDC	Bistable 2 coils	1-1462050-4	
HF3 47			24VDC		1-1462050-5	

te.com

©2024 TE Connectivity Ltd. All Rights Reserved.

TE Connectivity, TE connectivity (logo) and Every Connection Counts are trademarks owned or licensed by the TE Connectivity Ltd. family of companies. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

While TE has made every reasonable effort to ensure the accuracy of the information in this document, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any changes to the information contained herein without prior notice. TE Connectivity assumes only those obligations set forth in the terms and conditions for this product and shall in no event be liable for any incidental, indirect, or consequential damages arising out of the sale, resale, use, or misapplication of the product. TE expressly disclaims any implied warranties with respect to the information contained herein, including, but not limited to, implied warranties of merchantability or fitness for a particular purpose. Dimensions, specifications and/or information contained herein are for reference purposes only and are subject to change without notice. Consult TE for the latest dimensions, specifications and/or information. Users of TE Connectivity products must make their own assessment as to whether the respective product is suitable for the respective desired application.

07/24 ED

