

EKM-1261-1D2-4X16-2CG-C2 Art.-Nr.: F81424-000 (JOR-90961)

## **Fuse Box for Lighting Application EKM 1261**

For installation in lighting columns with minimum diameter of 100 mm With door opening minimum 80 x 250 mm

For outdoor application

1 fuse 25A / E 27

Terminal block with 5 mantle terminals:

2 cables 5 x 6- 16 mm<sup>2</sup>

Protection class II (with double or increased insulation)

With ingress protection IP 54

2 feeder cables Ø 22mm

2x compression gland PG 13,5 for luminar cables Ø7-14mm

(1x closed with a sealing disk)









