# Standard Power Timer contact for p.c.b

#### 1. Scope

#### 1.1 Contents.

This specification describes the design, the characteristic, the versions, the tests and the quality Requirements of the Standard power timer contact for p.c.b

#### 1.2 Product List.

Description	Applicable part number	
With Latch type	85047-1, 1-85047-1	
Without Latch type	368028-1, 1-368028-1	

Table 1

### 2. Applicable Documents.

The following documents form a part of this specification to the extent specified herein. In the case of a conflict between this specification and the specified documents, this specification has priority.

#### 2.1 Other Standards.

- A. JIS C5402, 5.3, 5.4: Measuring methods and testing procedures for electromechanical components.
- B. IEC 512-2, 2a, 2b: Contact resistance.
- C. JIS C5402, 6.6, 6.19: Mating and unmating force.

Rev "B"



#### Description.

#### 3.1 Contact Construct.




Fig 1

Body post shall be assembled at pcb hole with applicable insertion M/C Applicable mating tab size is 6.3 x 0.8mm, 5.8 x 0.8mm, 4.8 x 0.8mm.

### 3.2 Materials:

- A. Contact Body: pre-tinned CuNiSi Alloy.
- B. Cantilever Spring: Stainless steel.

## 4. Reguirements.

## 4.1 General Requirements.

All tests executed with the individual components must comply with the inspection plan in this Specification.

- Number of samples; Min. 10.
- Temperature Range; -40°c ~ +130°c.

### 4.2 Ratings.

Current carrying capacity	Max. 30A
Maximum mating cycles	10
Temperature range	-40°c ~ +130°c

Table 2



# **Product Specification**

108-61041 Rev B

## 4.3 Test Requirements.

## 4.3.1 Electrical & Mechanical Test procedure

NO	TEST DESCRIPTION	REQUIREMENTS	PROCEDURE	
1	Dimension Check	According to	Measure Item : Terminal Height	
		Product Drawing	From P.C.B Surface after assembly	
2	Resistance of assembled	Initial: 3 mΩ Max.	* Test Voltage on open circuit:	
}	Contact between Mated	After reliability	DC 13V	
	Tab and Recep Terminal	Test: 6 mΩ Max.	* Test Current : 1 A	
			Measure the Contact Resistance	
	·		According to IEC 512-2	
			(see Fig. 2)	
3	Mating and unmating	The following values	Measure the required force to mate &	
	Force	apply to the first mating	unmate counterpart gauge	
		Cycle:	tab with operating speed at	
		Mating force	25mm/min.	
		0.5 ~ 2.0 kgf		
		Unmating force 0.2 ~ 0.7 kgf	·	
4	Resistance to High	* must Satisfy 80% of	Expose mated contact under the	
<b>"</b>	Temperature.	initial tab Inser./Ext	temperature at 120± 2°C for 120 hours	
		Force.	lomporature at 1202 2 0 for 120 hours	
		* contact Resistance	·	
	i	6 mΩ Max.		
5	Current Cycle	Contact Resistance	Applied Current : 30 A	
	Current Cycle	6 mΩ Max.	Current Timing: 45 minutes "ON"	
		U IIIMA IVIAA.	15 minutes: "OFF" make this 1 cycle	
ĺ	·		Repeat 200 cycles at 25 °C.	
6	Temperature Rising	50℃ Max	Temperature of test Room:80°C	
		DO O Man	Test Current; 10, 15, 20, 25, 30A	
			Impose each current of mated contact	
			reaches to saturation Temperature.	
7	Vibration Test	Electrical	Temperature of test Room: 80℃	
	_	discontinuity	Test Current: 1 mA, 5V	
		10 μ sec Max	Vibration Frequency: 20 ~ 200 HZ	
		Contact Resistance	Vibration Acceleration: 4.4G	
		$6 \text{ m}\Omega$ Max.	Vibration Direction: X, Y, Z Axis.	
			Vibration Duration: 8 hours for	
			each Axis.	
<u> </u>	TT1	C-t-t-D-	Related Test procedure : AMP 109-5202	
8	Thermal Shock	Contact Resistance	high Temperature : 120 ℃ per 1h.	
		6 mΩ Max.	Low Temperature: -40°C per 1h.	
			Marking this a cycle, Repeat 60	
			Cycles.	
			Temperature exchange Time:	
			within 3 minutes after exchange Time,	
			the room temperature must be selled to	
			120°C± 3°C or -40°C ± 3°C Related	
		1	Test procedure : AMP 109-5103	

Table 3

Electronics




Fig. 2



## **Product Specification**

108-61041 Rev B

## 5. Revision History

Current Revision	New Revision	Changes	Reason for Change	EC No.
A	В	Revised	Material Change	FC00-0101-02

## 6. SPECIFICATION APPROVAL

Prepared by,

Y.M. Choi

Product Engineer

Approved by,

C.S. Lee

Product Engineering Manager

Checked By,

J.K. Song

Senior Product Engineer